










































































































































Overview of Functions and Codes (Alphabetical)














































The table below lists all available functions. If these functions have been configured (contact the service personnel), they can be called by entering a code or pressing a function key.






















































Functions		Operating Steps
Accept call	Directed	* 5 9 Int.
	Group	* 5 7
Adjust ring tone		(or) 2 simultaneously
Adjust ring volume		(or) 1 simultaneously
Answer call		
Assign station number (not for U.S.)		* 4 1 MSN Ext.
Associated dialing		* 6 7 Int. Stn No.
Associated service		* 8 3 Int.
Call charge assignment/account code		* 6 0 ACCT if appl. Ext.
Call forwarding	On	* 1 1 Stn No. * 1 2 Stn No. * 1 3 Stn No.
	Off	# 1
	Forward Line: On	* 5 0 1 Trk No. 1 Stn No. * 5 0 1 Trk No. 2 Stn No. * 5 0 1 Trk No. 3 Stn No.
	Forward Line: Off	# 5 0 1 Trk No.
	Call forwarding in carrier network on	* 6 4 1 MSN Ext.














		 * 6 4 2  MSN  Ext. 
		 * 6 4 3  MSN  Ext. 
	Call forwarding in carrier network off	 # 6 4 1   MSN 
		 # 6 4 2   MSN 
		 # 6 4 3   MSN 
	Call waiting (camp-on)	  Int.  Stn busy, wait 5 seconds
Callback	Store a callback	<input type="text" value="Callback"/> 
	Delete a callback	 # 5 8 
	Answering a callback (call)	
Camp-on	Accept a waiting call (camp-on)	 
	Terminate second call, resume first call	(1x or 2x) <input type="text" value="Consultation"/> 
	Prevent call waiting (automatic camp-on)	 # 4 9 0 
	Allow call waiting (automatic camp-on)	 * 4 9 0 
	Call waiting tone on	 # 8 7 
	Call waiting tone off	 * 8 7 
Change call number		 * 9 4 1 9  own call No.
		 Code # 9 4 1 9
Change call volume		 (+ or -) + - simultaneously
Conference	Start	  Stn No. <input type="text" value="Consultation"/> 
		 Stn No. <input type="text" value="Consultation"/>  * 3
	The other party does not respond 1. Continue the call	(1x or 2x) <input type="text" value="Consultation"/> 

	Add a party to the conference (max. five)	<div>Consultation   Stn No.</div> <div>Consultation  * 3 etc.</div>
	Leave conference	
	End conference	Consultation  # 3
	Remove ISDN central office party from the conference (only for U.S., not for HiPath 500)	Consultation  * 4 9 1
Consult		<div> Consultation   Stn No.</div> <div>(1x or 2x) Consultation </div> <div>Consultation  * 2</div> <div>Consultation  * 3</div> <div></div>
	Quit consultation, resume first call	
	Toggle	
	Start three-party conference	
	Connect parties	
Control relay	On (not for HiPath 500)	 * 9 0 1 ... 4 
	Off (not for HiPath 500)	 # 9 0 1 ... 4 
DND	On	 * 9 7 
	Off	 # 9 7 
Door opener	Conversation (entrance telephone)	 or after 30 seconds   Int.
	Open door	Consultation  * 6 1  Int.
	Door release on	 * 8 9  Int. + Code  (1 or 2)
	Door release off	 # 8 9  Int. 
DTMF dialing/Tone dialing		 Consultation  * 5 3 
Ending a call		 or Release 
Group call	Leave	 # 8 5  or
		 # 8 5 #  or

		  # 8 5  Group 
	Join	 * 8 5  or  * 8 5 #  or  * 8 5  Group 
HF answerback		
Hotline		
Making calls		  Stn No. or  Stn No. 
Message	Send	 * 6 8  Int. (0 ... 9) 
	Delete (sent)	 # 6 8 1 
	Answering	  # 6 8 3
Monitoring		 * 9 4 4  Int.
Mute	Off	 <input type="text" value="Mute"/> 
	On	 <input type="text" value="Mute"/> 
Night answer	On	 * 4 4  Int.  or  * 4 4 * 
	Off	 # 4 4 
Override		Stn busy <input type="text" value="Consultation"/>  * 6 2 
Paging	Paging another person (not for U.S., not for HiPath 500)	 * 4 5  Int. 
	Answer page (simple / enhanced paging equipment)	 * 5 9  Int. or
		 # 4 5  Int.
Park a call		 <input type="text" value="Consultation"/>  * 5 6 (0 ... 9)
	Retrieve a parked call	

		 # 5 6 (0 ... 9)
Phone	Changeover on (lock)	 * 6 6  Code
	Changeover off (unlock)	 # 6 6  Code
	Lock all phones	 * 9 4 3  Int. *
	Unlock all phones	 * 9 4 3  Int. #
Phone test		 * 9 4 0
Picking up (retrieving) a held call		 * 6 3  Line No.
Redial		 <input type="text" value="Redial"/> 
Reject call		<input type="text" value="Release"/> 
Reset services		 # 0 
Ring transfer	On	 * 5 0 2  Line No. 
	Off	 # 5 0 2  Line No. 
Ringing group	On	 * 8 1  Int. 
	Off	 # 8 1 
Room monitor	On	 * 8 8  
	Off	
	Monitoring a room	  Int.
Saving a PIN		 * 9 3  Old code  2x new code
Speaker call		 * 8 0  Int. 
Speed-dialing	Use speed-dialing	 <input type="text" value="Speed-dial"/>   (*0...*9 or 000...999) or
		 * 7  (*0...*9 or 000...999)
	Speed-dialing: store	

	station	 * 9 2  *0... *9  Ext. 
Suppress caller ID	On	 * 8 6 
	Off	 # 8 6 
Telephone data service (not for HiPath 500)		 Consultation  * 4 2 
Timed reminder	Save	 * 4 6  (Time e.g.0905) 
	Delete	 # 4 6 
	Accept timed call	 
Trace call (not for U.S.)		 Consultation  * 8 4
Transferring a call		 Consultation   Stn No. 
	...After announcement to group	 Consultation  * 8 0  Group 
Trunk flash (not for HiPath 500)		 Consultation  * 5 1 
Trunk	Reserve trunk	  Busy (external) Wait 5 seconds 
	When the reserved trunk is free	  Ext.
UCD	Log on at beginning of shift	 * 4 0 1  Code 
	Log off at end of shift	 # 4 0 1 
	Log off work	 # 4 0 2 
	Log on work	 * 4 0 2 
	Work time on	( or ) * 4 0 3 
	Work time off	( or ) # 4 0 3 
	Night answer on	 * 4 0 4 
	Night answer off	

	  4 0 4 
Using another phone like your own	  5 0 8  Int.  Code 
Using mailboxes	   6 8 3 or   Message Waiting 